SST1 Programming - step by step V2.0 (Basic + Extended)

LED	off	Step 1 slowly flashing	Step 2 faster flashing	Step 3 slowly flashing	Step 4 faster flashing	Step 5	Step 6 slowly flashing	Step 7 faster flashing	Step 8 slowly flashing
Press Button S2 -									
Pod	_	_	_	_	_			_	
Pro- pulsion	_	_	_	_	_				_
length of time	> 3 sec.	~ 12 sec.	~ 4 sec.	~ 5 sec.	~ 8 sec.	(mostly < 10 sec.)	until you press the button *	until you press the button	until you press the button
what to do	press the button until the LED starts to flash	let the joystick in the center- position	move the joystick into forward motion	move the joystick to the right (left) position **	go to all the positions of the joystick	automatic step - do nothing	bring the pod to standstill - therefore move to left or right position	bring the propulsion to standstill - therefore move to left or right position	bring the pod on headway - therefore move to left or right position

^{*} If DIP10 = On - automatic step over ~ 5 sec. / ** see user-manual